

TCXO/VC-TCXO HIGH STABILITY

TG - 5035CJ/CG/CE

•Frequency range : 13 MHz to 52 MHz (TG-5035CJ/CG)

10 MHz to 40MHz (TG-5035CE)

•Supply voltage : 1.8 V Typ./ 2.8 V Typ./ 3.0 V Typ./ 3.3 V Typ.

•Frequency / temperature characteristics

: $\pm 0.5 \times 10^{-6}$ Max or $\pm 2.0 \times 10^{-6}$ Max.

•Applications : GPS, RF,

Wireless communication devices (CDMA, WCDMA, LTE, WiMAX, other)

•Features : High stability, Stand-by function (ST)





Product Number (Please contact us)
TG-5035CJ: X1G003841xxxx00
TG-5035CG: X1G003851xxxx00
TG-5035CE: X1G003831xxxx00







TG-5035CJ TG-5035CG (2.0 × 1.6 × 0.73 mm) (2.5 × 2.0 × 0.8 mm)

TG-5035CE) (3.2 × 2.5 × 0.9 mm)

Actual size

TG-5035CJ	TG-5035CG	TG-5035CE


Specifications (characteristics)

Item	Symbol	VC-TCXO	TCXO	TCXO-Standby	Conditions / Remarks
	fo	13 MHz, 16.368 MHz, 16.369 MHz, 19.2 MHz,		Standard frequency	
Output frequency range		26 MHz, and 38.4 MHz			
		13.000 MHz to 52.000 MHz		TG-5035CJ/TG5035CG	
		10.000 MHz to 40.000 MHz		TG-5035CE	
Supply voltage	Vcc	1.8 V ±0.1 V / 2.8 V ±5% / 3.0 V ±5% / 3.3 V ±5%			Supply voltage range: 1.7 V to 3.6 V
Storage temperature	T_stg	-40 °C to +90 °C			Storage as single product.
Operating temperature	T_use	-40 °C to +85 °C / -30 °C to +85 °C			
Frequency tolerance	f_tol	±2.0 ×10 ⁻⁶ Max.			After reflow, +25 °C
Frequency/temperature characteristics	fo-Tc	±0.5 × 10 ⁻⁶ Max. / -30 °C to +85 °C		High stability version (for GPS)	
		±2.0 × 10 ⁻⁶ Max. / -30 °C to +85 °C		Standard stability version	
		±0.5 × 10 ⁻⁶ Max. / -40 °C to +85 °C		Customized product.(Option)	
Frequency/load coefficient	fo-Load	±0.2 × 10 ⁻⁶ Max.			10 kΩ // 10 pF ±10 %
Frequency/voltage coefficient	fo-Vcc	±0.2 ×10 ⁻⁶ Max.			Vcc ±5%
Frequency aging		±1.0 ×10 ⁻⁶ Max.		+25 ℃ , First year,10 MHz ≦fo≦40 MHz	
	f_age	±1.5 ×10 ⁻⁶ Max.		+25 ℃ , First year,40 MHz <fo≦52 mhz<="" td=""></fo≦52>	
Current consumption	Icc	1.5 mA Max.		10 MHz≦fo≦26 MHz	
Current consumption	ICC	2.0 mA Max.		26 MHz <fo≦52 mhz<="" td=""></fo≦52>	
Stand-by current	I_std	— 10 μA Max.		ST = GND	
Input voltage	V _{IH}	— 80% Vcc Min. — 20 % Vcc Max.		- ST terminal	
	V _{IL}				
Input resistance	Rin	500 kΩ Min. —		Vc- GND (DC)	
Frequency control range	f_cont				Vc =0.9 V ±0.6 V (Vcc =1.8 V) or
		$\pm 8.0 \times 10^{-6}$ to $\pm 15.0 \times 10^{-6}$		Vc =1.4 V ±1.0 V (Vcc =2.8 V) or	
				_	Vc =1.5 V ±1.0 V (Vcc =3.0 V) or
				Vc =1.65 V ±1.0 V (Vcc =3.3 V)	
Frequency change polarity	_	Positive polarity —			
Symmetry	SYM	40 % to 60 %			GND level (DC cut)
Output voltage	VPP	0.8 V Min.			Peak to Peak
Start-up time	t_str	2.0 ms Max.			T=0 at 90% Vcc
Output load condition	Load_R	10 kΩ 10 pF		DC cut capacitor = 0.01 μF	
	Load_C				

* Note : Please contact us for requirements not listed in this specification.

①Model ②Package type ③Spec segment (Please contact us) ④Frequenc

(Unit: mm) External dimensions <Bottom View> TG-5035CJ C0.15 , #3 TG-5035CG #1 C0.2 9:0 2.5±0.2 3.2±0.2 #3 TG-5035CE Connection VC-TCXO TCXO TCXO-Standby Pin C0.27 1 Vc N.C. ST OUT



(Unit: mm)

Footprint (Recommended)

To maintain stable operation, provide a 0.01uF to 0.1uF by-pass capacitor at a location as near as possible to the power source terminal of the crystal product (between Vcc - GND).

PROMOTION OF ENVIRONMENTAL MANAGEMENT SYSTEM CONFORMING TO INTERNATIONAL STANDARDS

At Seiko Epson, all environmental initiatives operate under the Plan-Do-Check-Action (PDCA) cycle designed to achieve continuous improvements. The environmental management system (EMS) operates under the ISO 14001 environmental management standard.

All of our major manufacturing and non-manufacturing sites, in Japan and overseas, completed the acquisition of ISO 14001 certification.

ISO 14000 is an international standard for environmental management that was established by the International Standards Organization in 1996 against the background of growing concern regarding global warming, destruction of the ozone layer, and global deforestation.

WORKING FOR HIGH QUALITY

In order provide high quality and reliable products and services than meet customer needs.

Seiko Epson made early efforts towards obtaining ISO9000 series certification and has acquired ISO9001 for all business establishments in Japan and abroad. We have also acquired ISO/TS 16949 certification that is requested strongly by major automotive manufacturers as standard.

ISO/TS16949 is the international standard that added the sector-specific supplemental requirements for automotive industry based on ISO9001.

Explanation of the mark that are using it for the catalog



►Pb free.



- ► Complies with EU RoHS directive.
 - *About the products without the Pb-free mark.

 Contains Pb in products exempted by EU RoHS directive.

 (Contains Pb in sealing glass, high melting temperature type solder or other.)



▶ Designed for automotive applications such as Car Multimedia, Body Electronics, Remote Keyless Entry etc.



 \blacktriangleright Designed for automotive applications related to driving safety (Engine Control Unit, Air Bag, ESC etc).

Notice

- This material is subject to change without notice.
- Any part of this material may not be reproduced or duplicated in any form or any means without the written permission of Seiko Epson.
- The information about applied data, circuitry, software, usage, etc. written in this material is intended for reference only. Seiko Epson
 does not assume any liability for the occurrence of customer damage or infringing on any patent or copyright of a third party. This
 material does not authorize the licensing for any patent or intellectual copyrights.
- When exporting the products or technology described in this material, you should comply with the applicable export control laws and regulations and follow the procedures required by such laws and regulations.
- You are requested not to use the products (and any technical information furnished, if any) for the development and/or manufacture of weapon of mass destruction or for other military purposes. You are also requested that you would not make the products available to any third party who may use the products for such prohibited purposes.
- These products are intended for general use in electronic equipment. When using them in specific applications that require extremely high reliability, such as the applications stated below, you must obtain permission from Seiko Epson in advance.
 - / Space equipment (artificial satellites, rockets, etc.) / Transportation vehicles and related (automobiles, aircraft, trains, vessels, etc.) / Medical instruments to sustain life / Submarine transmitters / Power stations and related / Fire work equipment and security equipment / traffic control equipment / and others requiring equivalent reliability.
- All brands or product names mentioned herein are trademarks and/or registered trademarks of their respective.