	Issue No.	:	151RJ00004103
	Date of Issue	:	February 6, 2004
Digi-Key	Classification	:	New Change Renewal

# PRODUCT SPECIFICATION FOR INFORMATION

Product Description	:	Thick Film Chip Resistor	
Product Part Number	:	ERJ1TYF***U, ERJ1TY0R00U	
Classification of Spec	:	Individual Product Spec	
Applications	:	Standard electronic equipment	
		For other applications, contact our person singed below.	
Term of Validity	:	February 5, 2009 from the date of issue	

CUSTOMER USE ONLY	Receipt Record # :
	Date of Receipt: :
	Received by :
	Title :
	Dept :

Matsushita Electronic Components Co.,Ltd. LCR Device Company	Prepared by : E	Engineering Department
Resistor Business Unit	Contact Person :	H.Yabukoshi
	Title :	
	Approved :	S.Hoshitoku
401 Sadamasa-cho, Fukui City, Fukui 910-8502 Japan	Title :	Manager of Engineering

Tel : Fukui (0776) 56-8034

Fax : Fukui (0776) 56-3114

	UCT SPECI	<ul> <li>(1) Substr</li> <li>(2) Protect</li> <li>(3) Resistities</li> <li>(4) Inner</li> <li>(5) Middlet</li> <li>(6) Outer</li> </ul>	DR IMFORMA ate : Alumina tive Coating : ive Element : Termination : Termination : unning change plating.	Resin Metal glaze Thick film m : Ni Plating Sn Plating	
	₩ ₩ (6)	<ul> <li>(2) Protec</li> <li>(3) Resisting</li> <li>(4) Inner</li> <li>(5) Middle</li> <li>(6) Outer</li> <li>* Under rest</li> </ul>	tive Coating : ive Element : Termination : Termination Termination : unning chang	Resin Metal glaze Thick film m : Ni Plating Sn Plating	aterial
	₩ ₩ (6)	<ul> <li>(2) Protec</li> <li>(3) Resisting</li> <li>(4) Inner</li> <li>(5) Middle</li> <li>(6) Outer</li> <li>* Under rest</li> </ul>	tive Coating : ive Element : Termination : Termination Termination : unning chang	Resin Metal glaze Thick film m : Ni Plating Sn Plating	aterial
	(6)	<ul> <li>(2) Protec</li> <li>(3) Resisting</li> <li>(4) Inner</li> <li>(5) Middle</li> <li>(6) Outer</li> <li>* Under rest</li> </ul>	tive Coating : ive Element : Termination : Termination Termination : unning chang	Resin Metal glaze Thick film m : Ni Plating Sn Plating	
	(6)	<ul> <li>(2) Protec</li> <li>(3) Resisting</li> <li>(4) Inner</li> <li>(5) Middle</li> <li>(6) Outer</li> <li>* Under rest</li> </ul>	tive Coating : ive Element : Termination : Termination Termination : unning chang	Resin Metal glaze Thick film m : Ni Plating Sn Plating	
< b >	∱t ⊻			ing form Sn/	Pb plating
1					
<b>–</b>	W	а	b	t	I
6.40+/-0.20 3.	.20+/-0.20	0.65+/-0.20	0.60+/-0.20	0.60+/-0.10	5.10+/-0.20
<ul> <li>2. Power Derating Curve</li> <li> <sup>120</sup> <sup>125</sup> <sup>126</sup> <sup>126</sup> <sup>127</sup> <sup>128</sup> <sup>128</sup> <sup>128</sup> <sup>129</sup> <sup>129</sup></li></ul>					
Potod vo	مايرم		Evolo	nation	
Item     Rated value       Power Rating     1.0W			ed at ambient wer rating sha	temperature all be detern	
0	Ambient <sup>-</sup> Rated va	40 -20 0 20 40 60 80 Ambient Temperature Fig	Ambient Temperature (deg.C) Rated value W deg.C, po accordance	Operation       Operation	Operating temperating temperating       Operating tempera

MATSUSHITA ELECTRONIC COMPONENTS Co., LTD

Subject Chip Resistor

Part No.

## PRODUCT SPECIFICATION FOR IMFORMATION

Spec. No.

## **ERJ1TYF**

14 - 2

151-SRJ-E7049B

Rated voltage &       below. And when the rated voltage exceeds the maximum RCWV, the maximum RCWV should be the rated voltage.         Working Voltage       Rated voltage = (Power rating x Resistance Value) <sup>1/2</sup> The maximum RCWV : 200V       The overload voltage should be 2.5 times the rated voltage. And when the voltage exceeds the maximum overload voltage, the maximum overload voltage.         Overload Voltage       The overload voltage should be 2.5 times the rated voltage. And when the voltage should be the overload voltage.         Resistance       The maximum overload voltage : 400V         Resistance       10 ohm – 1.0 M ohm (E-24 series)         Circuit board of use       You should use the aluminum or the ceramic substrate when the added wttage exceeds 0.5W.         3-2 Jumper       Item       Rated value       Explanation         Ratied current       2 A       deg.C, power rating shall be determined in accordance with Figure 1.         Overload current       4 A       Resistance value       Less than 50 m ohm         A.       Explanation of Part Number       1 T       Y       F       1 0 2       U	Item	Rated value	Explanation				
Rated Continuous       the maximum RCWV should be the rated voltage.         Working Voltage       Rated voltage = (Power rating x Resistance Value) <sup>1/2</sup> The maximum RCWV : 200V       The overload voltage should be 2.5 times the rated voltage. And when the voltage exceeds the maximum overload voltage.         Overload Voltage       The overload voltage should be the overload voltage.         Resistance       The maximum overload voltage : 400V         Resistance       10 ohm – 1.0 M ohm (E-24 series)         Circuit board of use       You should use the aluminum or the ceramic substrate when the added wttage exceeds 0.5W.         3-2 Jumper       Item         Rated current       2 A         Overload current       4 A         Resistance value       Less than 50 m ohm         Explanation of Part Number       11 T       Y         F       10 T       Y		The rated voltage of each resistance should be calculated from the equation					
Working Voltage       Rated voltage = (Power rating x Resistance Value) <sup>1/2</sup> The maximum RCWV : 200V         The overload voltage should be 2.5 times the rated voltage. And when the voltage exceeds the maximum overload voltage, the maximum overload voltage should be the overload voltage.         Overload Voltage         Resistance         Tolerance         F : +/- 1%         Resistance         To ohm - 1.0 M ohm (E-24 series)         Circuit board of         You should use the aluminum or the ceramic substrate when the added wttage exceeds 0.5W.         3-2 Jumper         Item       Rated value         Ratied current       2 A         Overload current       4 A         Resistance value       Less than 50 m ohm         Explanation of Part Number       11 T         Y       F       1 0 2       U	Rated voltage &	below. And when the rated voltage exceeds the maximum RCWV,					
The maximum RCWV : 200V         Overload Voltage         The overload voltage should be 2.5 times the rated voltage. And when the voltage exceeds the maximum overload voltage, the maximum overload voltage should be the overload voltage. The maximum overload voltage : 400V         Resistance       The maximum overload voltage : 400V         Resistance       10 ohm - 1.0 M ohm (E-24 series)         Circuit board of use       You should use the aluminum or the ceramic substrate when the added wttage exceeds 0.5W.         3-2 Jumper       Item         Ratied current       2 A         Qverload current       4 A         Resistance value       Less than 50 m ohm         Explanation of Part Number       Item T         Y       F       1       0       2         U       1       T       Y       F       1       0       2	Rated Continuous	the maximum RCWV should be the rated voltage.					
Overload Voltage       The overload voltage should be 2.5 times the rated voltage. And when the voltage exceeds the maximum overload voltage, the maximum overload voltage should be the overload voltage.         The voltage should be the overload voltage.       The maximum overload voltage is 400V         Resistance       F : +/- 1%         Resistance       10 ohm – 1.0 M ohm (E-24 series)         Circuit board of use       You should use the aluminum or the ceramic substrate when the added wttage exceeds 0.5W.         3-2 Jumper       Item         Ratied current       2 A         Qverload current       4 A         Resistance value       Less than 50 m ohm         Explanation of Part Number       1         Item       1         The resistor       1         Item       Item	Working Voltage	Rated voltage = (Power rating x Resistance Value) $1/2$					
Overload Voltage       the voltage exceeds the maximum overload voltage, the maximum overload voltage is voltage should be the overload voltage.         The maximum overload voltage : 400V         Resistance       F : +/- 1%         Tolerance       F : +/- 1%         Resistance       10 ohm – 1.0 M ohm (E-24 series)         Circuit board of use       You should use the aluminum or the ceramic substrate when the added wttage exceeds 0.5W.         3-2 Jumper       Item         Ratied current       2 A         Overload current       4 A         Resistance value       Less than 50 m ohm         Explanation of Part Number       Item J 1 T Y F 1 0 2 U		The maximum RCWV : 200V					
Overload Voltage       voltage should be the overload voltage.         The maximum overload voltage : 400V         Resistance         Tolerance         F : +/- 1%         Resistance         10 ohm – 1.0 M ohm (E-24 series)         Circuit board of use         Vou should use the aluminum or the ceramic substrate when the added use         wttage exceeds 0.5W.         3-2 Jumper         Item       Rated value         Explanation         When used at ambient temperature above deg.C, power rating shall be determined in accordance with Figure 1.         Overload current       4 A         Resistance value       Less than 50 m ohm         Explanation of Part Number         4-1 Resistor       I         E       R       I         I       T       Y         F       I       0       2	The overload voltage should be 2.5 times the rated voltage. And when						
voltage should be the overload voltage.         The maximum overload voltage : 400V         Resistance         Tolerance         F : +/- 1%         Resistance         10 ohm – 1.0 M ohm (E-24 series)         Circuit board of use         You should use the aluminum or the ceramic substrate when the added wttage exceeds 0.5W.         3-2 Jumper         Item       Rated value         Explanation         When used at ambient temperature above deg.C, power rating shall be determined in accordance with Figure 1.         Overload current       4 A         Resistance value       Less than 50 m ohm         Explanation of Part Number         I-1 Resistor       I         E       R         J       1         T       Y         F       1         O       2	Overload Voltage	the voltage exceeds the max	imum overload voltage, the maximum overload				
Resistance Tolerance       F : +/- 1%         Resistance       10 ohm – 1.0 M ohm (E-24 series)         Circuit board of use       You should use the aluminum or the ceramic substrate when the added wttage exceeds 0.5W.         3-2 Jumper       Item         Rated value       Explanation         Ratied current       2 A         Overload current       4 A         Resistance value       Less than 50 m ohm         Explanation of Part Number       1         It Resistor       I         E       R         J       1         T       Y         F       1         O       2	eveneda venage	voltage should be the overload	ad voltage.				
Tolerance       F : +/- 1%         Resistance       10 ohm – 1.0 M ohm (E-24 series)         Circuit board of use       You should use the aluminum or the ceramic substrate when the added wttage exceeds 0.5W.         3-2 Jumper       Item       Rated value       Explanation         Ratied current       2 A       When used at ambient temperature above deg.C, power rating shall be determined in accordance with Figure 1.         Overload current       4 A         Resistance value       Less than 50 m ohm         Explanation of Part Number       4.1 Resistor         E       R       J       1       T       Y       F       1       0       2       U		The maximum overload voltage : 400V					
Circuit board of use       You should use the aluminum or the ceramic substrate when the added wttage exceeds 0.5W.         3-2 Jumper       Item       Rated value       Explanation         Item       Rated value       Explanation         Ratied current       2 A       When used at ambient temperature above deg.C, power rating shall be determined in accordance with Figure 1.         Overload current       4 A         Resistance value       Less than 50 m ohm         E       R       J       T       Y       F       1       0       2       U		F : +/- 1%					
use       wttage exceeds 0.5W.         3-2 Jumper       Item       Rated value       Explanation         Item       Rated value       Explanation         Ratied current       2 A       When used at ambient temperature above deg.C, power rating shall be determined in accordance with Figure 1.         Overload current       4 A         Resistance value       Less than 50 m ohm         Explanation of Part Number       Image: Temperature above deg.C, power rating shall be determined in accordance with Figure 1.         Overload current       4 A         Resistance value       Less than 50 m ohm         Explanation of Part Number       Image: Temperature above deg.C, power rating shall be determined in accordance with Figure 1.         Image:	Resistance	10 ohm – 1.0 M ohm (E-24 series)					
B-2 Jumper       Rated value       Explanation         Item       Rated value       Explanation         Ratied current       2 A       When used at ambient temperature above deg.C, power rating shall be determined in accordance with Figure 1.         Overload current       4 A         Resistance value       Less than 50 m ohm         Explanation of Part Number       Integral         Item       Integral         Item </td <td>Circuit board of</td> <td colspan="5">You should use the aluminum or the ceramic substrate when the added</td>	Circuit board of	You should use the aluminum or the ceramic substrate when the added					
Item       Rated value       Explanation         Ratied current       2 A       When used at ambient temperature above deg.C, power rating shall be determined in accordance with Figure 1.         Overload current       4 A         Resistance value       Less than 50 m ohm         Explanation of Part Number         4-1 Resistor         E       R       J         1       T       Y         F       1       0       2	use	wttage exceeds 0.5W.					
Ratied current       2 A       When used at ambient temperature above deg.C, power rating shall be determined in accordance with Figure 1.         Overload current       4 A         Resistance value       Less than 50 m ohm         Explanation of Part Number         4-1 Resistor         E       R       J         1       T       Y         F       1       0       2	3-2 Jumper						
Ratied current       2 A       deg.C, power rating shall be determined in accordance with Figure 1.         Overload current       4 A         Resistance value       Less than 50 m ohm         Explanation of Part Number         4-1 Resistor         E       R       J       1       T       Y       F       1       0       2       U	ltem	Rated value	Explanation				
accordance with Figure 1.       Overload current     4 A       Resistance value     Less than 50 m ohm       Explanation of Part Number       4-1 Resistor       E     R       J     1       T     Y       F     1       0     2			When used at ambient temperature above 70				
Overload current       4 A         Resistance value       Less than 50 m ohm         . Explanation of Part Number         4-1 Resistor         E       R       J       1       T       Y       F       1       0       2       U	Ratied current	2 A	deg.C, power rating shall be determined in				
Resistance value       Less than 50 m ohm         Explanation of Part Number         4-1 Resistor         E       R       J       1       T       Y       F       1       0       2       U			accordance with Figure 1.				
ERJI 1 TYFI 0 2 U	Overload current	4 A					
4-1 Resistor <u>E R J 1 T Y F 1 0 2 U</u>	Resistance value	Less than 50 m ohm					
4-1 Resistor <u>E R J 1 T Y F 1 0 2 U</u>							
E R J 1 T Y F 1 0 2 U	Explanation of Par	t Number					
	I-1 Resistor						
(1) (2) (3) (4) (5) (6)	(1)	(2) (3)	(4) (5) (6)				

- (1) Product Code : Thick Film Chip Resistor
- (2) Size and Rated Power : 6.4 mm x 3.2mm, 1.0 W
- (3) Marking : Marking on Black Side
- (4) Resistance Tolerance

Code	Resistance Tolerance
F	+/- 1%

Subject		Spec. No.				
Chip Resistor	Resistor PRODUCT SPECIFICATION FOR IMFORMATION					
Part No.						
	ERJ1TYF	14 - 3				
(5) Resistance	Value					
The first	two digits are the significant figures of resistance value, and the	last figure shows				
the numbe	r of zero following in ohm.					
(6) Packaging	Configuration					
Code	Packaging Configuration					
U Taping (4000pcs/reel)						
4-2 Jumper						
E R J 1 T Y 0 R 0 0 U						
(1)	(2) (3) (4) (5)	_				
(1) Product Co	de : Thick Film Chip Resistor					
(2) Size and R	ated Power : 6.4mm x 3.2 mm					
(3) Resistance	value					
Code Resistance value						
0R00 Jumper (Less than 50 m ohm)						
(4) Packaging	Configuration					
Code	Packaging Configuration					
U	Taping (4000pcs/reel)					

# 5. Appearance & Construction

Item	Rated value	Explanation			
Appearance & Construction	<ul> <li>fade easily. The surface of and discoloration.</li> <li>2. The electrode should be properties of the plating should not fact pinhole, projection and distered and the element.</li> <li>4. Dimensions of the substrational distered and the sub</li></ul>	connected electrically, mechanically to resistive te should be as in the list and it should not and crack. Details of appearance criteria shall			
As far as there s	As far as there shall not designation especially, the following tests and measurement shall be				
operated under the following conditions.					
Normal temperation	Normal temperature : 5 deg.C to 35 deg.C				

Normal humidity : 45 % to 85 %

Normal atmospheric pressure : 86 k Pa to 106 k Pa

Chip Resistor Part No.

## PRODUCT SPECIFICATION FOR IMFORMATION

Spec. No.

151-SRJ-E7049B

Γc	art NO.	EF	RJ1TYF		14 - 4	
6. Performance Specification						
	ltem	Item Specification Resistor Jumper		Test Method (JIS-C5201-1)		
	nem				.5201-1)	
		DC resistance val	ue shall			
	DC resistance	be within the spe	cified	At 20 deg.C, 65%RH		
		tolerance.				
				Natural resistance change pe	er temperature	
				degree centigrade.		
	Temperature			$TCR = (R_2 - R_1)x10^6/R_1(t_2 - t_1)$	(x10 <sup>-6</sup> /deg.C)	
	coefficient	10 ohm – 1 M o	ohm	$R_1$ : Resistance value at	reference	
	of resistance	: +/- 200 x 10 <sup>-4</sup>	ී/deg.C	temperature (t <sub>1</sub> )		
	(TCR)			R <sub>2</sub> : Resistance value at	test	
				temperature (t <sub>2</sub> )		
				$t_1$ : 25 deg.C , $t_2$ : 125	deg.C	
	Short time	ΔR :	Less than	Resistors shall be applied 2.	5 times the rated	
	overload		50m ohm	voltage for 5 seconds.		
	ovendau	+/-(2%+0.1ohm)		Max. overload voltage shall t	be 400V.	
				Resistors shall be subjected	to 10000 cycles	
	Intermittent	ΔR :	Less than	of 2.5 times the rated voltag	e applied for 1	
	overload	Δκ +/-(5%+0.1ohm)	50m ohm	second with pause of 25 sec	conds between	
	ovendau	+/-(3 /0+0.101111)		tests.		
				Max. overload voltage shall t	be 400V.	
				AC 400V between substrate	and termination	
		No evidence of flag	ashover,	for 1 minute.		
	Dielectric	mechanical dama	mechanical damage, arcing	AC powe supply	AC power	
	Withstanding	or insulation brea			supply	
					or	
ł					Insulation	
					resistance	
	Insulation	Min. 1000 M ohm			meter	
	resistance			Resistors shall be facing dow	vn.	
				After applying DC 400V to the resistor,		
				insulation resistance shall be	measured.	

Chip Resistor Part No.

## PRODUCT SPECIFICATION FOR IMFORMATION

Spec. No.

#### 151-SRJ-E7049B

ERJ1TYF

14 - 5

ltom	Specification	Test Method (US CE201.1)
Item	Resistor Jump	Test Method (JIS-C5201-1)
	10 ohm – 1k ohm	
	: 0 dB (1.0 µV/\	()
	1.1k ohm – 9.1k ohm	Noise shall be measured by RESISTOR
Noise	: 10 dB (3.2 μV/\	/) NOISE TEST SET MODEL 315C by
	10k ohm – 91k ohm	Quan-Tech Div.
	: 15 dB (5.6 μV/\	/) Max. V <sub>R</sub> shall be 35 dB.
	100k ohm – 910k ohm	
	: 20 dB (10 μV/V	)

7. Machinery characteristic

ltem	Specifica	tion	Test Method (JIS-C5201-1)	
nem	Resistor	Jumper		
Terminal strength	Min. 4.9 N (500g)		Cupper plate : t=0.4mm Pull speed : 10mm/s Fixed Solder Sample Copper plate	
Bending	No mechanical damage.		Substrate : Glass epoxy (t=1.6 mm) Span : 90mm Bending distance : 2mm (10 seconds) <test pattern=""> 1.85 5.2 1.85 4.0 (mm)</test>	
strength	∆R : +/-(1%+0.05ohm)	Less than 50m ohm		

Chip Resistor Part No.

# PRODUCT SPECIFICATION FOR IMFORMATION 151-SRJ-E7049B

Spec. No.

## ERJ1TYF

14 - 6

Itom	Specification			
Item	Resistor	Jumper	Test Method (JIS-C5201-1)	
Solderability	Termination should be covered uniformly with solder (Min. 95% coverage)		Resistors shall be dipped in the melted solder bath at 235 deg.C +/- 5 deg.C for 2 seconds +/- 0.5 second. Flux shall be removed from the surface of termination with clean organic solvent.	
Resistance to soldering heat	∆R : +/-(1%+0.05ohm)	Less than 50m ohm	Resistors shall be dipped in the melted solder bath at 270 deg.C +/- 3 deg.C for 10 seconds +/- 1 second.	
Resistance to vibration (Low frequency)	∆R : +/-(1%+0.05ohm)	Less than 50m ohm	Resistors shall be subjected to a single vibration having as double amplitude of 1.5 mm in 3 directions perpendicular one another for 2 hours each. (6 hours in total) The vibration frequency shall be varied uniformly from 10 Hz to 55 Hz, and return to 10 Hz traversing for 1 min.	
Resistance to	Without distinct deformation in appearance		Solvent solution : Isopropyl alcohol (1)Dipping 10 +/- 1 hours, dry in room condition for 30 +/- 10 minutes.	
solvent	∆R : +/-(0.5% +0.05ohm)	Less than 50m ohm	(2)Ultrasonic wave washing : 5 +/- 1 min. (0.3W/cm,28kHz) Dry in room condition for 30 +/-10 minutes.	

### Subiect Chip Resistor

Part No.

PRODUCT SPECIFICATION FOR IMFORMATION

151-SRJ-E7049B

ERJ1TYF

14 - 7

### 8. Environmental test

ltem	Specification		Test Method (JIS-C5201-1)	
lleni	Resistor	Jumper		
Low temperature exposure	∆R : +/-(1%+0.05ohm)	Less than 50m ohm	Resistors shall be exposed at -55 deg.C +/- deg.C with no load for 1000 hours +48/-0 hours.	
Low temperature Operating	∆R : +/-(1%+0.05ohm)	Less than 50m ohm	Resistors shall be placed at -65 deg.C +/- deg.C for 1.5hours. After applying RCWV for 45 minutes, resistors shall be exposed in ro condition for 8 hours +/- 1 hour.	
High temperature exposure	∆R : +/-(1%+0.05ohm)	Less than 50m ohm	Resistors shall be exposed at 125 deg.C +/- deg.C with no load for 1000 hours +48/-0 hours.	
Temperature cycling	∆R : +/-(1%+0.05ohm)	Less than 50m ohm	Resistors shall be tested for 5 cycles continuously in accordance with the following duty cycle.StepTemperature (deg.C)Time (min.)1-55 +/-3302Room temperatureMax. 33+125 +/-3304Room temperatureMax.3	
Humidity (Steady state)	∆R : +/-(1%+0.05ohm)	Less than 50m ohm	Resistors shall be exposed at 60 deg.C +/- deg.C and 90% to 95% relative hummidity a humidity test chamber for 1000 hours +48 hours.	
Salt spray	∆R : +/-(1%+0.05ohm)	Less than 50m ohm	Spray 5 +/- 1 wt% salt water for 96 +/- 4 hours at 35 +/-2 deg.C.	
Load life	∆R: +/-(3%+0.1ohm)	Less than 50m ohm	Resistors shall be operated at DC rated pow (1.5 hours "ON", 0.5 hours "OFF") for 1000 hours +48/-0 hours in a test chamber controlled at 70 deg.C +/-2 deg.C.	
Load life in humidity	∆R : +/-(3%+0.1 ohm)	Less than 50m ohm	Resistors shall be operated at DC rated pow (1.5 hours "ON", 0.5 hours "OFF") for 1000 hours +48/-0 hours in a test chamber controlled at 60 deg.C +/- 2 deg.C and at 90 % to 95% in relative hummidity.	

Chip Resistor Part No.

# PRODUCT SPECIFICATION FOR IMFORMATION

Spec. No.

## ERJ1TYF

14 - 8

151-SRJ-E7049B

ltom	Specification			
Item	Resistor	Jumper	Test Method (JIS-C5201-1)	
Boiling test	∆R : +/-(1%+0.05ohm)	50m ohm	Soak in boiling water for 1 +/- 0.1 hour. Resistors shall be exposed at room condition for 30 minuites.	

#### 9. Other characteristics

Item	Specification	Test method	
Surface Temperature rise	Less than 50 deg.C	Resistors shall be mouted on the Ceramic substrate (t=1.0mm). And the hot spot temperarure rise of chip resistor shall be measured when applied the rated power. Applied voltage must not exceed maximun RCWV.	

#### 10. Resistance value Marking

Express resistance value on resin side with three digits.



<Example>

<u>123 = 12k ohm</u>

000 = Chip jumper

The first two digits should be significant figures of resistance for E-24 series and the third one denotes number of zeros.

Subiect Chip Resistor

Part No.

#### PRODUCT SPECIFICATION FOR IMFORMATION

Spec. No.

#### 151-SRJ-E7049B

#### **ERJ1TYF**

14 - 9

## 11. Common precautions in handling resistors

	Notice for use
(1) Thi	s specification shows the quality and performance of a unit component. Before adoption
be	sure to evaluate and verify the product mounting it in your product.
(2) We	take no responsibility for troubles caused by the product usage that is not specified in
this	s catalog. Be sure to exchange the delivery specification with us.
is hui equ cor equ	e fail-safe design and ensure safety by carrying out the following items in cases where it forecast that the failure of the product gives serious damage to something important like man life, for instant in traffic transportation equipment (trains, cars, traffic signal uipment, etc.), medical equipment, aerospace equipment, electric heating appliances, mbustion and gas equipment, rotating equipment, disaster and crime preventive uipment.
	nsure safety as the system by setting protective circuits and protective equipment.
	nsure safety as the system by setting such redundant circuits as do not cause danger by single failure.
. ,	en a dogma shall be occurred about safety for this product, be sure to inform us rapidly, erate your technical examination.
•	e product is designed to use in general standard applications of general electric
	uipment (AV products, household electric appliances, office equipment, information and
COI	mmunication equipment, etc.); hence, it do not take the use under the following special vironments into consideration.
Ac	cordingly, the use in the following special environments, and such environmental
	nditions may affect the performance of the product; prior to use, verify the performance, iability, etc. thoroughly.
1)	Use in liquids such as water, oil, chemical, and organic solvent.
2)	Use under direct sunlight, in outdoor or in dusty atmospheres.
	Use in places full of corrosive gases such as sea breeze, $CI_2$ , $H_2S$ , $NH_3$ , $SO_2$ , and $NO_X$ . Use in environment with large static electricity or strong electromagnetic waves.
5)	Where the product is close to a heating component, and where an inflammable such as a polyvinyl chloride wire is arranged close to the product.
	Where the resistor is sealed or coated with resin, etc.
7)	Where water or a water-soluble detergent is used in cleaning free soldering and in flux cleaning after soldering (Pay particular attention to soluble flux.)
(6) If ti	ransient load (heavy load in a short time) like pulse is expected to be applied, carry out
eva	aluation and confirmation test with resistors actually mounted on your own board. When
the	e load of more than rated power is applied under the load condition at steady state, it
ma	ay impair performance and/or reliability of resistor. Never exceed the rated power. When

Subject		Spec. No.			
Chip Resistor	PRODUCT SPECIFICATION FOR IMFORMATION	151-SRJ-E7049B			
Part No.	ERJ1TYF	14 - 10			
<ul> <li>(7) Halogen type (C recommended a</li> <li>(8) When soldering the soldering in time as short a</li> <li>(9) Avoid physical s pliers or tweeze resistor's perfor</li> </ul>	n of chip resistor in solvent for long time. Use solvent afte	is not stors. stor with a tip of ature, solder for a tool (a pair of tor and may affect			
solderability may be (1) Storage in place (2) Storage in place (3) Storage in place range of 45 %F (4) The period of g	<ul> <li>If the product is stored in the following environments and conditions, the performance and solderability may be badly affected, avoid the storage in the following environments.</li> <li>(1) Storage in places full of corrosive gases such as sea breeze, Cl<sub>2</sub>, H<sub>2</sub>S, NH<sub>3</sub>, SO<sub>2</sub>, and NO<sub>x</sub>.</li> <li>(2) Storage in places exposed to direct sunlight.</li> <li>(3) Storage in places outside the temperature range of 5 deg.C to 35 deg.C and humidity range of 45 %RH to 85 %RH.</li> <li>(4) The period of guarantee for performance such as solderability is 1 year after our delivery; and this condition applies only to the case where the storage method specified in item 3) has been</li> </ul>				
the Montreal Pr (2) All materials use Examination and (3) All the materials flame-retardant. (4) If you need the	s not been manufactured with any ozone-depleting chemica	erning the O <sub>s</sub> or PBB <sub>s</sub> as the			

Subject		Spec. No.		
Chip Resistor	PRODUCT SPECIFICATION FOR IMFORMATION	151-SRJ-E7049B		
Part No.				
	ERJ1TYF	14 - 11		
14. Receipt and Valid	time limit for Product Specification for Information			
(1) Be sure to retu	rn a copy to our company after stamping your company ac	cceptance.		
If you shall not	return a copy by 3 months which a valid time limit of listing	ng shall expire, we		
judge that you	shall receive this specification.			
(2) By 3 months th	at a valid time limit of listing shall expire, if there shall not	offering it by letter,		
a valid time limi	t shall continue every 1 year.			
If an alteration s	shall be done on the way futher more, a former specification	on shall become		
invalid.	invalid.			
15. Production site				
* Country : Japan				
Plant : Fukui Matsushita Electric Co.,Ltd.				
* Country : Malaysia				
Plant : Matsushita Electronic Device (M) Sdn. Bhd. <medem></medem>				
* Country : China				
Plant : Tianjin Matsushita Electronic Components Co.,Ltd. <tmcom></tmcom>				



- 16-3-1 Taping
  - (1) Minimum Bending Radius

When Carrier tape shall be bent by Minimum Bending Radius (15mm), no defection of chip and no break of carrier tape. However minimum bending radius shall be tested for 1 time.

(2) Resistance to climate

When resistors shall be exposed at 60 deg.C, 90 to 95 %RH for 120 hours, no defection of chip and no break of carrier tape.

When the top tape shall be peeled tape should not have flash and tear.



1)Customer name, 2)Part name, 3)Part number, 4)Customer part number, 5)Quantity 6)Maker name, 7)Poduction country

Chip Resistor Part No.

# PRODUCT SPECIFICATION FOR IMFORMATION

Spec. No.

151-SRJ-E7049B

ERJ1TYF

14 - 14

17. Appearance Quality Criteria					
Item	Figure	Appearance quality criteria	Remark		
Protective coating Chipping	W A B C	A≤W/4 B≤C/2	Chipping on both sides shall be considered defective		
Terminal Chipping		A≤W/4 B≤Terminal width			
Pin hole	->+< \$ >->-	One pin hole / chip resistor ¢ ≤ 0.2 mm	Pin hole penetrates The resistive material.		
Flash	A	A≤0.1 mm			
Top terminal Lacking		A≤W/4			
Side terminal Lacking		A≤W/4			
Protective coating and terminal aberration		Protective coating and terminal aberration shall be within the terminal width dimension			
Marking		Marking must be reada	ble.		