

**PLEASE CHECK WWW.MOLEX.COM FOR LATEST PART INFORMATION**

**Part Number:** [130153-0163](#)  
**Status:** **Active**  
**Overview:** [Outlet Boxes](#)  
**Description:** Super-Safeway® In-Line Industrial GFCI, Manual Reset, NEMA L5-30, 30A, 120V, 0.61m Cord Length

**Documents:**

[RoHS Certificate of Compliance \(PDF\)](#)

**Agency Certification**

CSA	LR6837
UL	E66308

**General**

Product Family	Power Distribution
Series	<a href="#">130153</a>
Enclosure Rating	NEMA 6P
GFCI Reset	Manual
Open Neutral Relay	Yes
Overview	<a href="#">Outlet Boxes</a>
Product Name	Super-Safeway™
Receptacle Type	N/A
Type	GFCI Industrial Duty
UPC	78678835072
Woodhead	Yes

**Physical**

Cord Diameter	13.00mm (.512")
Cord Grip Body Size	Internal Double C-Clamp
Cord Length	0.61m (2.0' )
Feed-Thru	Yes
Flip Lid	No
Material - Housing	Nylon
Number of Receptacles	0
Packaging Type	Carton

**Electrical**

Cord Type	10/3 SJTW
Current - Maximum per Contact	30A
GFCI	Yes-In-line
Ground Continuity Monitor	No
NEMA Configuration	NEMA L5-30
Voltage - Maximum	240V

**Material Info**

Old Part Number	30051-1
-----------------	---------



**EU RoHS**

**China RoHS**

**Compliance Status**

**Not Reviewed**

**REACH SVHC**

**Not Reviewed**

**Low-Halogen Status**

**Not Reviewed**

**Need more information on product environmental compliance?**

Email [productcompliance@molex.com](mailto:productcompliance@molex.com)  
 For a multiple part number RoHS Certificate of Compliance, [click here](#)

Please visit the [Contact Us](#) section for any non-product compliance questions.

**Search Parts in this Series**

[130153Series](#)