

# NOT RECOMMENDED

SELECTION GUIDE

## **NMXU Series**

FOR NEW DESIGNATEd 5W Single & Dual Output DC/DC Converters



#### **FEATURES**

- RoHS compliant
- Single or dual output
- 1kVDC isolation
- Pin compatible with NMXSO series
- Power density 0.85W/cm<sup>3</sup>
- UL 94V-0 package material
- Footprint 5.88cm<sup>2</sup>
- Industry standard pinout
- 5V & 12V input
- 5V, 12V & 15V output
- No heatsink required
- Internal SMD construction
- Fully encapsulated with toroidal magnetics
- No external components required
- PCB mounting

#### DESCRIPTION

The NMXU series of DC/DC converters is particularly suited to isolating and/or converting DC power rails. The galvanic isolation allows the device to be configured to provide an isolated negative rail in systems where only positive rails exist. The devices are particularly suited for use in distributed power systems where there is low variation in the bus voltage levels.

Order Code	Nominal Input Voltage	Output Voltage	Output Current	Efficiency (Typ.)	Isolation Capacitance (Typ.)	MTTF <sup>1</sup>	Recommended Alternative
	V	V	А	%	pF	kHrs	
NMXD0505UC	5	±5	±0.5	75	31.5	779	
NMXD0512UC	5	±12	±0.208	75	33	158	
NMXD0515UC	5	±15	±0.167	75	34.2	86	
NMXD1205UC	12	±5	±0.5	75	34.7	233	NCS6D1205C
NMXD1212UC	12	±12	±0.208	75	52.9	107	NCS6D1212C
NMXD1215UC	12	±15	±0.167	75	59.9	68	NCS6D1215C
NMXS0505UC	5	5	1.0	75	30.6	792	
NMXS0512UC	5	12	0.417	75	31.2	158	
NMXS0515UC	5	15	0.333	75	32.6	86	
NMXS1205UC	12	5	1.0	75	32.5	233	NCS6S1205C
NMXS1212UC	12	12	0.417	75	51.9	107	NCS6S1212C
NMXS1215UC	12	15	0.333	75	54.1	68	NCS6S1215C

When operated **with** additional external load capacitance the rise time of the input voltage will determine the maximum external capacitance value for guaranteed start up. The slower the rise time of the input voltage the greater the maximum value of the additional external capacitance for reliable start up.

INPUT CHARACTERISTICS						
Parameter	Conditions	Min.	Тур.	Max.	Units	
Valtana ranga	Continuous operation, 5V input types	4.5	5.0	5.5	v	
Voltage range	Continuous operation, 12V input types	10.8	12.0	13.2	v	
Reflected ripple voltage	BW=DC to 20MHz, all output types			200	mV	

OUTPUT CHARACTERISTICS							
Parameter	Conditions	Min.	Тур.	Max.	Units		
Rated Power	$T_A = 0^{\circ}C$ to $70^{\circ}C$			5.0	W		
Voltage Set Point Accuracy	See tolerance envelope						
Line regulation	High VIN to low VIN		1.1		%/%		
Load Degulation	10% load to rated load, 5V output types		7	12	%		
Load Regulation	10% load to rated load, 12V & 15V output types		5	7.5	70		
Ripple and Noise	BW=DC to 20MHz, all output types			125	mV p-p		

#### ABSOLUTE MAXIMUM RATINGS

Short-circuit protection <sup>2</sup>	1 second
Lead temperature 1.5mm from case for 10 seconds	300°C
Input voltage Vℕ, NMXU05 types	7V
Input voltage VIN, NMXU12 types	15V

1. Calculated using MIL-HDBK-217F with nominal input voltage at full load.

2. Supply voltage must be disconnected at the end of the short circuit duration.

All specifications typical at TA=25°C, nominal input voltage and rated output current unless otherwise specified.



www.murata-ps.com/support

### muRata Ps Murata Power Solutions

# **NMXU Series**

#### Isolated 5W Single & Dual Output DC/DC Converters

ISOLATION CHARACTERISTICS						
Conditions	Min.	Тур.	Max.	Units		
Flash tested for 1 second	1000			VDC		
Viso= 1000VDC	1			GΩ		
	Conditions Flash tested for 1 second	Conditions     Min.       Flash tested for 1 second     1000	Conditions     Min.     Typ.       Flash tested for 1 second     1000	Conditions     Min.     Typ.     Max.       Flash tested for 1 second     1000     1000		

GENERAL CHARACTERISTICS					
Parameter	Conditions	Min.	Тур.	Max.	Units
Switching frequency	All input types		70		kHz

TEMPERATURE CHARACTERISTICS					
Parameter	Conditions	Min.	Тур.	Max.	Units
Specification	All output types	0		70	
Storage		-55		100	°C
Case temperature rise above	5V output types		30		0
ambient	All other output types		20		
Cooling	Free air convection				

#### **TOLERANCE ENVELOPE**



#### **RoHS COMPLIANCE INFORMATION**



This series is compatible with RoHS soldering systems with a peak wave solder temperature of 300°C for 10 seconds. The pin termination finish on this product series is Matte Tin over Nickel Preplate. The series is backward compatible with Sn/Pb soldering systems.

For further information, please visit www.murata-ps.com/rohs

#### **TECHNICAL NOTES**

#### **ISOLATION VOLTAGE**

'Hi Pot Test', 'Flash Tested', 'Withstand Voltage', 'Proof Voltage', 'Dielectric Withstand Voltage' & 'Isolation Test Voltage' are all terms that relate to the same thing, a test voltage, applied for a specified time, across a component designed to provide electrical isolation, to verify the integrity of that isolation.

Murata Power Solutions NMXU series of DC/DC converters are all 100% production tested at their stated isolation voltage. This is 1kVDC for 1 second.

A question commonly asked is, "What is the continuous voltage that can be applied across the part in normal operation?"

For a part holding no specific agency approvals, such as the NMXU series, both input and output should normally be maintained within SELV limits i.e. less than 42.4V peak, or 60VDC. The isolation test voltage represents a measure of immunity to transient voltages and the part should never be used as an element of a safety isolation system. The part could be expected to function correctly with several hundred volts offset applied continuously across the isolation barrier; but then the circuitry on both sides of the barrier must be regarded as operating at an unsafe voltage and further isolation/insulation systems must form a barrier between these circuits and any user-accessible circuitry according to safety standard requirements.

#### **REPEATED HIGH-VOLTAGE ISOLATION TESTING**

It is well known that repeated high-voltage isolation testing of a barrier component can actually degrade isolation capability, to a lesser or greater degree depending on materials, construction and environment. The NMXU series has toroidal isolation transformers, with no additional insulation between primary and secondary windings of enameled wire. While parts can be expected to withstand several times the stated test voltage, the isolation capability does depend on the wire insulation. Any material, including this enamel (typically polyurethane) is susceptible to eventual chemical degradation when subject to very high applied voltages thus implying that the number of tests should be strictly limited. We therefore strongly advise against repeated high voltage isolation testing, but if it is absolutely required, that the voltage be reduced by 20% from specified test voltage.

This consideration equally applies to agency recognized parts rated for better than functional isolation where the wire enamel insulation is always supplemented by a further insulation system of physical spacing or barriers.

## muRata Ps Murata Power Solutions

# **NMXU Series**





# PIN CONNECTIONS Single Output Variants Dual Output Variants Pin Function Pin Function

Isolated 5W Single & Dual Output DC/DC Converters

1 11 1	runcuon	1 11 1	runcuon
1	-Vin	1	Vin
2	+VIN	2	+Vin
3	+Vоит	3	+Vоит
4	Not fitted	4	Common
5	-Vout	5	-Vout

#### RECOMMENDED FOOTPRINT DETAILS



Murata Power Solutions, Inc. 11 Cabot Boulevard, Mansfield, MA 02048-1151 U.S.A. ISO 9001 and 14001 REGISTERED



0.417 (10.6)

This product is subject to the following <u>operating requirements</u> and the <u>Life and Safety Critical Application Sales Policy</u>: Refer to: <u>http://www.murata-ps.com/requirements/</u>

Murata Power Solutions, Inc. makes no representation that the use of its products in the circuits described herein, or the use of other technical information contained herein, will not infringe upon existing or future patent rights. The descriptions contained herein do not imply the granting of licenses to make, use, or sell equipment constructed in accordance therewith. Specifications are subject to change without notice. @2013 Murata Power Solutions, Inc.

#### www.murata-ps.com/support

Not to scale.

All dimensions in inches  $\pm 0.01$  (mm  $\pm 0.25$ mm).